

- (2) When cleaning the display surface use a soft cloth (eg gauze) with a solvent (recommended below) and wipe lightly:
 - isopropyl alcohol
 - ethyl alcohol
 - trichlorotrifluoroethane
- (3) Do not wipe the display surface with dry or hard materials that will damage the polarizer surface.
- (4) Do not use the following solvents:
 - water
 - ketone
 - aromatics
- (5) The LCD modules use CMOS LSI drivers and it is recommended that the body, work/assembly areas, and assembly equipment is grounded to protect against static electricity.
- (6) Avoid intense shock and falls from a height which would damage LCD elements.
- (7) To prevent modules from degradation, do not operate or store them exposed to direct sunshine or high temperature/humidity.

3.2 EPROM Substitution

- 3.2.1 It is possible that some service centres may wish to replace the 1 Mbit ROM compatible EPROM with EPROMs conforming to the JEDEC pinout. This requires a small modification to the board involving the interchange of pins 2 and 24. This applies to both the Z88 and the EPROM PACK. In order to modify the Z88, proceed as follows:
 - (a) Cut the track in one place and add three wire links as shown in Figure 4.1(a).
 - (b) Cut two tracks as shown in Figure 4.1(b).
- 3.2.2 In the case of the EPROM card, add external wiring to transpose pins 2 and 24.