

3.2.3 A summary of the action required for the various manufacturers' products is set out in the table below.

EPROM MAKE/TYPE	SWAP PINS 2 AND 24 ON 128k EPROM CARD?	MODIFY Z88 or OKAY AS IS?	ROM or JEDEC?
<u>Toshiba</u>  TC571000D-20 TC571001D-20	  YES NO	  MODIFY OK	  JEDEC ROM
<u>NEC</u>  uPD27C1000D-20 uPD27C1001D-20	  NO YES	  OK MODIFY	  ROM JEDEC
<u>Hitachi</u>  HN27C101G-20 HN27C301G-20	  YES NO	  MODIFY OK	  JEDEC ROM

NOTE: The NEC and Toshiba parts are opposite types  
but with similar part numbers